PCEI R5 Installation Guide

Introduction

•

- Deployment Architecture
- Pre-Installation Requirements
 - Recommended Hardware Requirements
 - Network Requirements
 - Software Prerequisites
- Installation High-Level Overview
 - Deployment Guide
 - Install CentOS on Host Server
 - Prepare Host Server for EMCO Deployment
 - Step 1. Enable sudo without entering sudo password
 - Step 2. Add sudo user to wheel group Step 3. Enable nested virtualization
 - Step 4. Install VNC Server (Optional)
 - Step 5. Modify libvirt bridge IP and route mode
 - Deploy EMCO

- Step 1. Generate SSH Keys
- Step 2. Download software and install EMCO
- Step 3. Monitor the installation
 - Step 4. Install Controller Blueprint Archives (CBA)
 - Update CDS py-executor
 - Kubernetes Cluster Registration CBA
 - Terraform Executor CBA
 - Helm Chart Processor CBA
 - Composite App Deployment Processor CBA
- Deploy Edge Clusters
 - Step 1. Edit VM creation script.
 - Step 2. Deploy two Edge Cluster VMs.
 - Step 3. Setup worker clusters inside VMs
- Modify sshd_config on VMs
- Deployment Verification
 - EMCO Deployment Verification
 - Edge Cluster Deployment Verification
- Uninstall Guide
- License
- References

Introduction

This document describes steps required to deploy a sample environment for the Public Cloud Edge Interface (PCEI) Blueprint.

Deployment Architecture

The deployment architecture is shown below. All Addressing and naming shown are for example purposes only.



Deployment environment components:

- 1. One Host Server
- 2. One Edge Multi-Cluster Orchestrator VM
- 3. Two Edge K8S Cluster VMs
- 4. Internal network connectivity to the Host Server and to the VMs

Pre-Installation Requirements

Recommended Hardware Requirements

Requirement	Value
CPU	18 Core / 36 vCPU
RAM	128 GB
DISK	500 GB
NETWORK	1 Gbps NIC Port

Network Requirements

- Internal Lab Network (RFC 1918 space)
- Internet access (NAT'd)
- IP routing in the Lab Network to reach VM interfaces

Software Prerequisites

Requirement	Value
Server OS	CentOS 7.x or above
VM OS	Ubuntu 18.04
Upstream SW	Refer to Deployment Guide Section

Installation High-Level Overview

The installation/deployment process consists of the following steps:

- 1. Install CentOS on Host Server.
- 2. Prepare Host Server for EMCO Deployment.
- 3. Deploy EMCO.
- 4. Deploy Edge Clusters.

Deployment Guide

Install CentOS on Host Server

- 1. Connect to Host Server iLO interface.
- 2. Start Virtual Console.
- 3. Mount Virtual Media with CentOS 7 ISO.
- 4. Install CentOS
 - a. Assign correct IP address, Subnet, Gateway and DNS to the NIC.
 - b. Include OpenSSH Server.
 - c. Install KVM/virtualization.
 - d. Add a user with admin privileges: onaplab user is used in this guide.

Prepare Host Server for EMCO Deployment

Step 1. Enable sudo without entering sudo password

```
sudo -i
visudo
# Uncomment the line below
%wheel ALL=(ALL) NOPASSWD: ALL
```

Step 2. Add sudo user to wheel group

usermod -aG wheel onaplab

Step 3. Enable nested virtualization

```
# Login as super user
sudo -i
# Check for the following parameter
cat /sys/module/kvm_intel/parameters/nested
Ν
# If it is Y, there is nothing else to be done. It is already enabled!
# If it is N, do the following:
# Edit /etc/default/grub file, and include kvm-intel.nested=1
GRUB_CMDLINE_LINUX parameter
GRUB_CMDLINE_LINUX="crashkernel=auto
console=ttyS0,38400n8,kvm-intel.nested=1"
# Rebuild your GRUB configuration
sudo grub2-mkconfig -o /boot/grub2/grub.cfg
# Enable nested KVM capabilities in /etc/modprobe.d/kvm.conf
# By uncommenting the below line
options kvm_intel nested=1
### Reboot the server
reboot
# Now, we should have the nested KVM capabilities enabled
cat /sys/module/kvm_intel/parameters/nested
Y
```

Step 4. Install VNC Server (Optional)

Follow instructions at:

https://www.tecmint.com/install-and-configure-vnc-server-in-centos-7/

Step 5. Modify libvirt bridge IP and route mode

This will allow connecting to VMs and pods directly from the Lab Network. Please replace the sample IPs with your IP addresses. Please replace the interface name (eno24 used in the example) with you server's interface name.

```
cat <<\EOF >> netdefault.xml
<network>
 <name>default</name>
  <br/><br/>dge name="vmbr0"/>
  <forward mode='route' dev='eno24'/>
 <ip address="10.121.7.129" netmask="255.255.255.224">
   <dhcp>
      <range start="10.121.7.144" end="10.121.7.158"/>
    </dhcp>
 </ip>
</network>
EOF
sudo virsh net-list
sudo virsh net-destroy default
sudo virsh net-undefine default
sudo virsh net-define netdefault.xml
sudo virsh net-start default
sudo virsh net-autostart default
```

Add necessary routes to your Lab Network routers. The example below assumes the the Host Server IP address is 10.121.1.12:

```
ip route 10.121.7.128 255.255.255.224 10.121.1.12
```

Deploy EMCO

Step 1. Generate SSH Keys

```
# Run commands below on the Host Server
ssh-keygen
cd ~/.ssh
chmod 600 id_rsa
chmod 600 id_rsa.pub
chmod 700 config
chmod 600 known_hosts
cat id_rsa.pub >> authorized_keys
chmod 600 authorized_keys
echo "# Increase the server timeout value" >> ~/.ssh/config
echo "ServerAliveInterval 120" >> ~/.ssh/config
```

Step 2. Download software and install EMCO

Note that the install process will:

- Deploy a VM amcop-vm-01
- Create a K8S cluster inside the VM
- Deploy EMCO components on the K8S cluster
- Deploy ONAP components on the K8S cluster

```
#### On the Host Server
sudo yum install -y git deltarpm
mkdir -p amcop_deploy
cd amcop_deploy
## Download the installation package zip file
wget --load-cookies /tmp/cookies.txt "https://docs.google.com/uc?export=download&confirm=$(wget --quiet --save-
cookies /tmp/cookies.txt --keep-session-cookies --no-check-certificate 'https://docs.google.com/uc?
export=download&id=1PMyc8yULDeTIY0xNvY0RDf_7CSWvli31' -0- | sed -rn 's/.*confirm=([0-9A-Za-z_]+).*/\1\n/p')
&id=1PMyc8yULDeTIY0xNvY0RDf_7CSWvli31" -O amcop_install_v2.0.zip && rm -rf /tmp/cookies.txt
unzip amcop_install_v2.0.zip
sudo chown -R onaplab:onaplab ~/amcop_deploy/
cd ~/amcop_deploy/aarna-stream/util-scripts
./prep_baremetal_centos.sh
####### Install EMCO/AMCOP
# Edit inventory.ini file. Use IP address of Host Server and the username.
cd ~/amcop_deploy/aarna-stream/amcop_deploy/ansible/deployment
vi inventory.ini
[deployment_host]
10.121.1.12 ansible_user=onaplab
nohup ansible-playbook ./main.yml -i inventory.ini -e deployment_env=on-prem -e jump_host_user=onaplab --
private-key=/home/onaplab/.ssh/id_rsa -e vm_user=onaplab &
```

Step 3. Monitor the installation

```
# On the Host Server

cd /home/onaplab/aarna-stream/anod_lite/logs
[onaplab@os12 logs]$ ls -1

total 1980

-rw-r--r--. 1 root root 510417 Nov 24 07:06 cluster_setup.log

-rw-r--r--. 1 root root 2019 Nov 24 06:54 create_vm.log

-rw-r--r--. 1 root root 1366779 Nov 24 07:15 deploy_emco_components.log

-rw-rw-r---. 1 root root 138233 Nov 24 07:35 deploy_onap.log

-rw-rw-rw-r--. 1 onaplab onaplab 83 Nov 24 06:53 README.md

tail -f create_vm.log

tail -f cluster_setup.log

tail -f deploy_emco_components.log

tail -f deploy_onap.log
```

If Install fails and you need to restart, please do the cleanup steps below on the Host Server.

```
sudo virsh destroy amcop-vm-01
sudo virsh undefine amcop-vm-01
sudo virsh pool-destroy amcop-vm-01
sudo virsh pool-undefine amcop-vm-01
sudo rm /var/lib/libvirt/images/amcop-vm-01/amcop-vm-01-cidata.iso
sudo rm /var/lib/libvirt/images/amcop-vm-01/amcop-vm-01.qcow2
```

Step 4. Install Controller Blueprint Archives (CBA)

Update CDS py-executor

https://gitlab.com/akraino-pcei-onap-cds/equinix-pcei-poc

Kubernetes Cluster Registration CBA

https://gitlab.com/akraino-pcei-onap-cds/equinix-pcei-poc/-/tree/main/cds-blueprints/emco-api-executor

Terraform Executor CBA

https://gitlab.com/akraino-pcei-onap-cds/equinix-pcei-poc/-/tree/main/cds-blueprints/terraform-plan-executor

Helm Chart Processor CBA

https://gitlab.com/akraino-pcei-onap-cds/equinix-pcei-poc/-/tree/main/cds-blueprints/helm-chart-processor

Composite App Deployment Processor CBA

https://gitlab.com/akraino-pcei-onap-cds/equinix-pcei-poc/-/tree/main/cds-blueprints/composite-app-deployment-processor

Deploy Edge Clusters

Step 1. Edit VM creation script.

```
# On the Host Server
cd /home/onaplab/amcop_deploy/aarna-stream/util-scripts
# Add "--cpu host" option to the end of the below line
vi create_qem_vm.sh
virt-install --connect qemu:///system --name $vm_name --ram $(($mem << 10)) --vcpus=$vCPU --os-type linux --os-
variant $os_variant --disk path=/var/lib/libvirt/images/$vm_name/"$vm_name".qcow2,format=qcow2 --disk /var/lib
/libvirt/images/$vm_name/$vm_name-cidata.iso,device=cdrom --import --network network=default --noautoconsole --
cpu host
# Save the file
```

Step 2. Deploy two Edge Cluster VMs.

These commands will create two Ubuntu 18.04 VMs with 100G Disk, 8 vcpu and 16G RAM and will copy the contents of the ~/.ssh/id_rsa.pub key file from the Host Server to the VMs' ~/.ssh/authorized_keys file.

sudo ./create_qem_vm.sh 2 edge_k8s-1 100 8 16 ubuntul8.04 \$HOME/.ssh/id_rsa.pub onaplab sudo ./create_qem_vm.sh 2 edge_k8s-2 100 8 16 ubuntul8.04 \$HOME/.ssh/id_rsa.pub onaplab

Step 3. Setup worker clusters inside VMs

```
# Find VM's IP addresses. On the Host Server run:
[onaplab@os12 ~]$ sudo virsh list --all
Id Name
                            State
_____
б
    amcop-vm-01
                            running
9
    edge_k8s-1
                            running
   edge_k8s-2
10
                            running
[onaplab@os12 ~]$ sudo virsh domifaddr edge_k8s-1
Name MAC address Protocol Address
_____
                                              -----
vnet1 52:54:00:19:96:72 ipv4 10.121.7.152/27
[onaplab@os12 ~]$
[onaplab@os12 ~]$ sudo virsh domifaddr edge_k8s-2
Name MAC address Protocol Address
_____
vnet2 52:54:00:c0:47:8b ipv4
                                  10.121.7.146/27
# ssh to each VM from the Host Server:
ssh onaplab@10.121.7.152
ssh onaplab@10.121.7.146
# Perform the following tasks in each VM:
sudo apt-get update -y
sudo apt-get upgrade -y
sudo apt-get install -y python-pip
git clone https://git.onap.org/multicloud/k8s/
# Run script to setup KUD clusters
nohup k8s/kud/hosting_providers/baremetal/aio.sh %
```

```
If the edge cluster deployment fails for any reason, please do the clean up steps below before you retry:
```

```
### Cleanup
sudo virsh destroy edge_k8s-1
sudo virsh undefine edge_k8s-1
sudo virsh pool-destroy edge_k8s-1
sudo virsh pool-undefine edge_k8s-1
sudo rm /var/lib/libvirt/images/edge_k8s-1/edge_k8s-1-cidata.iso
sudo rm /var/lib/libvirt/images/edge_k8s-1/edge_k8s-1.qcow2
sudo virsh destroy edge_k8s-2
sudo virsh undefine edge_k8s-2
sudo virsh pool-destroy edge_k8s-2
sudo virsh pool-destroy edge_k8s-2
sudo virsh pool-undefine edge_k8s-2
sudo rm /var/lib/libvirt/images/edge_k8s-2/edge_k8s-2-cidata.iso
sudo rm /var/lib/libvirt/images/edge_k8s-2/edge_k8s-2.qcow2
```

Modify sshd_config on VMs

To ensure that user onaplab can successfully ssh into EMCO and edge cluster VMs, add user onaplab to the sshd_config file.

```
## ssh to each VM:
ssh onaplab@10.121.7.152
sudo -i
cd /etc/ssh
vi sshd_config
AllowUsers ubuntu onaplab
```

Save the changes and exit the file

Deployment Verification

EMCO Deployment Verification

Perform the following steps to verify correct EMCO deployment:

```
# Determine IP address of EMCO VM:
[onaplab@os12 ~]$ sudo virsh list --all
Id Name
                             State
_____
6
    amcop-vm-01
                             running
9
     edge_k8s-1
                             running
   edge_k8s-2
10
                             running
[onaplab@os12 ~]$ sudo virsh domifaddr amcop-vm-01
Name MAC address Protocol Address
_____
      52:54:00:1a:8e:8b ipv4
vnet0
                                   10.121.7.145/27
# ssh to EMCO VM. You should be able to ssh without specifying the key:
[onaplab@os12 ~]$ ssh onaplab@10.121.7.145
# Verify K8S pods:
onaplab@emco:~$ kubectl get pods --all-namespaces
                                                READY STATUS RESTARTS AGE
NAMESPACE NAME
kube-system calico-kube-controllers-6f954885fb-bb2mr
                                                1/1 Running 0 28d
                                                                        28d
kube-system calico-node-ldcpv
                                                1/1
                                                     Running 0
kube-system coredns-6b968665c4-6558h
                                                                       28d
                                                       Running 0
                                                 1/1
          coredns-6b968665c4-rq6bf
                                                 0/1
                                                       Pending 0
                                                                        28d
kube-system
kube-system
          dns-autoscaler-5fc5fdbf6-njch7
                                                 1/1
                                                       Running
                                                                0
                                                                         28d
                                                1/1
                                                                        28d
kube-system
          kube-apiserver-nodel
                                                       Running
                                                                0
                                                               0
kube-system kube-controller-manager-nodel
                                                1/1
                                                       Running
                                                                        28d
                                                 1/1
                                                              0
kube-system kube-proxy-gg95d
                                                       Running
                                                                         28d
```

kube-system	kube-scheduler-node1		1/1	Runnin	g 0	28d
kube-system	kubernetes-dashboard-6c7466966c-	cjpxm	1/1	Runnin	.g 0	28d
kube-system	nodelocaldns-7pxcs		1/1	Runnin	.g 0	28d
kube-system	tiller-deploy-8756df4d9-zq52m		1/1	Runnin	.g ()	28d
onap	dev-cassandra-0		1/1	Runnin	g U g O	280 28d
onap	dev-cassandra-2		1/1	Runnin	a ()	28d
onap	dev-cds-blueprints-processor-6d6	97cc4d6-wzlfj	0/1	Init:1	/3 0	28d
onap	dev-cds-db-0		1/1	Runnin	.g 0	28d
onap	dev-cds-py-executor-7dcdc5f7f6-t	pfmg	1/1	Runnin	.g 0	28d
onap	dev-cds-sdc-listener-f99d4588d-n	t2tk	0/1	Init:0	/1 4021	28d
onap	dev-cds-ui-7768bb4b-cfbzd		1/1	Runnin	.g 0	28d
onap	dev-mariadb-galera-0		1/1	Runnin	.g 0	28d
onap	dev-mariadb-galera-1		1/1	Runnin	.g U a O	280
onap4k8s	clm-668c45d96d-99gpb		1/1	Runnin	a 0	28d
onap4k8s	emcoui-57846bd5df-c774f		1/1	Runnin	.g 0	28d
onap4k8s	etcd-768d5b6cc-ptmmr		1/1	Runnin	g 0	28d
onap4k8s	middleend-6d67c9bf54-tvs7s		1/1	Runnin	g 0	28d
onap4k8s	mongo-7988cb488b-kf29q		1/1	Runnin	.g 0	28d
onap4k8s	ncm-9f4b85787-nqnlm		1/1	Runnin	.g 0	28d
onap4k8s	orchestrator-5fd4845f8f-qsxlf		1/1	Runnin	.g 0	28d
onap4k8s	ovnaction-1794165b6-w85ms		1/1	Runnin	.g U ~ 0	28d
опарчков	rsync-/d9151bd9b-1/2sp		1/1	Rummin	.g U	280
# Verify K8S	services:					
onaplab@emco:	~\$ kubectl get svcall-namespac	es				
NAMESPACE	NAME	TYPE	CLUSTER	-IP	EXTERNAL-IP	PORT
(S)		AGE				
default	kubernetes	ClusterIP	10.233.	0.1	<none></none>	443
/TCP	a outo da a	28d	10 222	0 2	(2000)	E2/IIDD E2/MOD 01E2
/TCP	28d	Clusterip	10.233.	0.5	<none></none>	53/UDP,53/ICP,9153
kube-system	kubernetes-dashboard	ClusterIP	10.233.	35.188	<none></none>	443
/TCP		28d				
kube-system	tiller-deploy	ClusterIP	10.233.	33.249	<none></none>	44134
/TCP		28d				
onap	cassandra	ClusterIP	None		<none></none>	7000/TCP,7001/TCP,
/199/TCP,9042	/TCP,9160/TCP,61621/TCP 28d	ClusterTD	10 222	1 210	(nono)	F701
/TCP	cus-bideprints-processor-cruster	28d	10.235.	1.219		5701
onap	cds-blueprints-processor-grpc	ClusterIP	10.233.	34.1	<none></none>	9111
/TCP		28d				
onap	cds-blueprints-processor-http	ClusterIP	10.233.	31.74	<none></none>	8080
/TCP		28d				
onap	cds-db	ClusterIP	None		<none></none>	3306
/TCP		28d	10 000	12 240		
Unap /TCP	28d	Clusterip	10.233.4	43.240	<none></none>	50052/ICP,50053
onap	cds-sdc-listener	ClusterIP	10.233.	2.48	<none></none>	8080
/TCP		28d				
onap	cds-ui	NodePort	10.233.	55.19	<none></none>	3000:30497
/TCP		28d				
onap	mariadb-galera	ClusterIP	None		<none></none>	3306
/TCP	~] m	28d	10 222		(2000)	0061.21056
опаряков /тср	eim	28d	10.233.	59.50	<none></none>	9001.31020
onap4k8s	emcoui	NodePort	10.233.	2.5	<none></none>	9080:30480
/TCP		28d				
onap4k8s	etcd	ClusterIP	10.233.	54.80	<none></none>	2379/TCP,2380
/TCP	28	d				
onap4k8s	middleend	NodePort	10.233.	11.225	<none></none>	9891:31289
/TCP		28d	10 000	10 122		02012
onap4k8s /TCD	mongo	ClusterIP	10.233.	19.133	<none></none>	27017
onap4k8s	ncm	NodePort	10.233.	16.20	<none></none>	9031:32737
/TCP		28d		-	-	-
onap4k8s	orchestrator	NodePort	10.233.	23.25	<none></none>	9015:31298
/TCP		28d				
onap4k8s	ovnaction	NodePort	10.233.	37.45	<none></none>	9053:32514/TCP,9051:
3TTAT/J.Cb	28d					

onap4k8	s rsynd	2		NodePort 28d	10.233.60.47	<none></none>	9041:30555	
/ 101				200				
Access EM	Access EMCOUI GUI:							
# Determine EMCOUL Service Port:								
onaplab@emco:~\$ kubectl get svc emcoui -n onap4k8s								
NAME	TYPE	CLUSTER-IP	EXTERNAL-IP	PORT(S)	AGE			
emcoui	NodePort	10.233.2.5	<none></none>	9080:30480/TC	P 28d			
# To connect to EMCOUI GUI use IP address of amcop-vm-01 and port 30480								

To connect to EMCOUI GUI use IP address of amcop-vm-01 and port 30480:

http://10.121.1.52:30480



Edge Cluster Deployment Verification

To verify deployment of Edge Clusters, perform the following steps:

Determine Edge Cluster VM IP addresses: [onaplab@os12 ~]\$ sudo virsh list --all Id Name State _____ _____ 6 amcop-vm-01 running 9 edge k8s-1 running 10 edge_k8s-2 running [onaplab@os12 ~]\$ sudo virsh domifaddr edge_k8s-1 Name MAC address Protocol Address _____ vnet1 52:54:00:19:96:72 ipv4 10.121.7.152/27 [onaplab@os12 ~]\$ sudo virsh domifaddr edge_k8s-2 Name MAC address Protocol Address _____ _____ vnet2 52:54:00:c0:47:8b ipv4 10.121.7.146/27 # ssh to each VM from the Host Server. You should be able to ssh without specifying the key: ssh onaplab@10.121.7.152 ssh onaplab@10.121.7.146 # Perform the following tasks inside the VMs: onaplab@localhost:~\$ kubectl get pods --all-namespaces READY STATUS RESTARTS AGE NAMESPACE NAME cmk-rpgd7 2/2 Running 0 28d kube-system coredns-dff8fc7d-2xwrk 0/1 Pending 0 28d kube-system kube-system coredns-dff8fc7d-q2gcr 1/1 Running 0 28d dns-autoscaler-66498f5c5f-2kzmv 1/1 Running 0 28d kube-system 1/1 28d kube-system kube-apiserver-localhost Running 0 kube-controller-manager-localhost kube-system 1/1 Running 0 28d 1/1 Running 0 28d kube-system kube-flannel-8rm9p kube-system kube-multus-ds-amd64-mt9s5 1/1 Running 0 28d kube-system kube-proxy-ggk8m 1/1 Running 0 28d kube-scheduler-localhost kubernetes-dashboard-84999f8b5b-48xjq kubernetes-metrics-scraper-54fbb4d595-rw649 local-volume-provisioner-bmkc6 virtlet-vk7jl kube-scheduler-localhost1/1kubernetes-dashboard-84999f8b5b-48xjq1/1kubernetes-metrics-scraper-54fbb4d595-rw6491/1 Running 0 28d kube-system kube-system Running 0 28d kube-system 0 28d Running 1/1 Running 0 kube-system 28d 3/3 Running 0 28d kube-system node-feature-discovery nfd-master-78nms 1/1 28d Running 0 1/1 node-feature-discovery nfd-worker-k4d5g Running 45 28d 1/1 Running 0 28d operator nfn-agent-zlp9g operator nfn-operator-b768877d8-vcx7v 1/1 Running 0 28d 1/1 Running 0 operator ovn4nfv-cni-4c6rx 28d # Verify connectivity to EMCO Cluster onaplab@localhost:~\$ ping 10.121.7.145 PING 10.121.7.145 (10.121.7.145) 56(84) bytes of data. 64 bytes from 10.121.7.145: icmp_seq=1 ttl=64 time=0.457 ms 64 bytes from 10.121.7.145: icmp_seq=2 ttl=64 time=0.576 ms

Uninstall Guide

Perform the following steps to remove EMCO and Edge Clusters from the Host Server:

```
sudo virsh destroy amcop-vm-01
sudo virsh undefine amcop-vm-01
sudo virsh pool-destroy amcop-vm-01
sudo virsh pool-undefine amcop-vm-01
sudo rm /var/lib/libvirt/images/amcop-vm-01/amcop-vm-01-cidata.iso
sudo rm /var/lib/libvirt/images/amcop-vm-01/amcop-vm-01.qcow2
sudo virsh destroy edge_k8s-1
sudo virsh undefine edge_k8s-1
sudo virsh pool-destroy edge_k8s-1
sudo virsh pool-undefine edge_k8s-1
sudo rm /var/lib/libvirt/images/edge_k8s-1/edge_k8s-1-cidata.iso
sudo rm /var/lib/libvirt/images/edge_k8s-1/edge_k8s-1.qcow2
sudo virsh destroy edge_k8s-2
sudo virsh undefine edge_k8s-2
sudo virsh pool-destroy edge_k8s-2
sudo virsh pool-undefine edge_k8s-2
sudo rm /var/lib/libvirt/images/edge_k8s-2/edge_k8s-2-cidata.iso
sudo rm /var/lib/libvirt/images/edge_k8s-2/edge_k8s-2.qcow2
sudo rm -rf ~/amcop_deploy
sudo rm -rf ~/aarna_stream
```

License

References

AMCOP 2.0 Quickstart Guide (Bare Metal) - EMCO Install Guide by Aarna Networks AMCOP 2.0 User Guide - EMCO Config Guide by Aarna Networks