

MEC Architecture

Maciej Muehleisen Ericsson (ERI) maciej.muehleisen@ericsson.com

31st of May / 7th of June 2021, 5GCroCo Lunchtime Web-Seminar 6 (Hosted by 5G-PPP)



The project has received funding from the European Union's Horizon 2020 research and innovation programme under grant agreement No 825050-5GCroCo





5G Cross Border Control

Innovation Action H2020-ICT-18-2018 Contract 825050

Cooperative, Connected and Autonomous Mobility (CCAM) a 5G-PPP Phase III Project



The project has received funding from the European Union's Horizon 2020 research and innovation programme under grant agreement No 825050-5GCroCo



Before we Start...

- This presentation is being recorded and recording will be shared with registered participants (passwordprotected link)
- Slides will be shared
- We'll continue same time next week; please watch the recording if you missed Part I



Outline Part I

- About me
- Overview Deliverable D3.2
- Related Work
- Session Continuity: 3GPP Gateway Switching
- MEC with Cross-border / -MNO Handover
- More, if time allows



About Me

Key research interest: Modelling, design, evaluation, and certification of highly reliable / safety critical communication systems

- 2008 2012 ComNets RWTH Aachen University
 - Open Wireless Network Simulator developer
 - PhD research on "VoIP Performance of LTE Networks: VoLTE versus OTT" (2015)
- 2012 2016 ComNets Hamburg University of Technology (TUHH)
 - Group leader "Mobile & Vehicular Communication" (focus on aviation, maritime)
 - Sometimes acting group leader for "Sensor Networks and IoT" & "Future Internet and Network Planning"
- Since 2017 Ericsson Research Germany
 - Research Area "Networks" Master Researcher Industry Verticals Coordination (focus on automotive)
 - Coordination of tech. work in external associations (5GAA, AECC, ETSI-ITS) and projects (5GCroCo, 5GMOBIX, 5G-ROUTES, ART-04 SHOW)
 - Deputy Technical Coordinator 5GCroCo & leader of WP3 "Architecture"
- Very eager to discuss with other "experts" who want to deep dive into this under whatever "formal roof" (5G-PPP, 5GAA, AECC, ...)





Overview Deliverable D3.2

Outline (extract):

- Related Technical Specifications and Studies and their Applicability
 - 3GPP
 - Automotive Edge Computing Consortium (AECC)
 - Cloud Native Computing Foundation (CNCF)
- Interface Between MEC and 3GPP Network
- Session Continuity when Switching Gateways
- End-to-end Service Continuity when Switching MEC-hosts and/or Gateways
- Cross-MNO Inter-MEC Communication
- Relation to other Key 5G Solutions
 - Cross-border / -MNO Handover
 - Network Orchestration and Control
- Use Case Specific Solutions
 - HD Mapping
 - Anticipated Cooperative Collision Avoidance (ACCA)



Fifth Generation Cross-Border Control

Deliverable D3.2 Intermediate E2E, MEC & Positioning Architecture

Version: v1.0 2021-01-31

DISCLAIMER: This 5GCroCo D3.2 deliverable is not yet approved by the European Commission.

This project has received funding from the European Union's Horizon 2020 research and innovation programme under grant agreement No 825050. Any 5GCroCo results reflects only the authors' view and the Commission is thereby not responsible for any use that may be made of the information it contains.






D3.2: Section 4.3 "MEC"




Related Technical Specifications and Studies


- 3GPP:
 - RAN: Triggers like Tracking Area Updates (TAUs) can be used for gateway/server switching
 - SA2:
 - Session & Service Continuity (SSC) mode*) 1 – 3
 - Multi-homed PDU session (combined with SSC)
 - AF influence on traffic steering API
 - SA5: Use definition of roles described there (next slide)
- End-to-end service continuity to be solved by means of IETF





Related Technical Specifications and Studies: 3GPP SA5





Adjusted based on <u>5GAA V2X Application Layer Reference Architecture</u> (omitted VRU as not relevant for 5GCroCo)

Adapted some terms; added "WAN Provider" and app. software providers

RTA: Road Traffic Authority

SP: Service Provider



Related Technical Specifications and Studies: Cloud Native Computing Foundation (CNCF)


MEC is not all new but should be seen as subtopic of Cloud ecosystem incl. common tools / APIs / principles defined by CNCF:

- Public, private and hybrid clouds:
 - Role of MNO as "hybrid cloud" provider
 - Cooperation with Hyperscale Cloud Providers (Amazon Web Services (AWS), Microsoft Azure, ...)
- Containers (Kubernetes): Lightweight virtualization instead of (Kernel) VMs ((K)VMs); full tool chain (develop, test, deploy, ...)
- Microservices: Independent, distributed software pieces delivering the overall service
- Service meshes: Automatic discovery, interconnection and fail-over between the microservices
- <u>Immutable infrastructure:</u> Do not change parts of containers but deploy new ones when change is needed → Seamlessly integrated through service mesh; easy rollback on failure
- Declarative APIs:
 - E.g.: "Provide me HD maps as I go", "Assure I am always connected to the best Application Server to receive Hazard Warnings"
 - Instead of several calls (Imperative API): "Connect, initialize, select topics of interest, request change of server, ..."



Related Technical Specifications and Studies: AECC (Technical Report 2.0)

- AECC considers 3GPP 5G NSA and SA as network architecture
- Key issue #1 solutions:
 - Connect MEC hosts through SGi (NSA) / N6 (SA) interfaces
 - Different APNs/DNNs¹⁾
 can be used to route to
 MEC / central servers
 - Uplink classifier can also be used
- SSC (gateway / server switching) hardly covered in AECC




1) APN: Access Point Name (4G EPC, 5G NSA) DNN: Data Network Name (5G SA)



Related Technical Specifications and Studies: AECC (Technical Report 2.0)


- AECC considers 3GPP 5G NSA and SA as network architecture
- Key issue #2 solutions:
 - DNS, but need to define how DNS server obtains vehicle location information (later slides)
 - Lookup table in vehicle
 - IP anycast possible but not preferred (needs rarely enabled transport network support)





Session Continuity: 3GPP Gateway Switching


- 3GPP as basic architecture
- Similar for 5G NSA with other Network Function (NF) and interface names
- · Color codes nodes:
 - Blue: Physical NF
 - Green: Virtual NF (incl. containerized (cloud native))
 - Red: Virtualized / containerized (cloud native) application
- Color codes interfaces:
 - Blue: 3GPP control / management plane
 - Black: 3GPP user plane
 - Red: Not (yet) defined in 3GPP



Session Continuity: 3GPP Gateway Switching

SA / NSA:


- SSC mode 1 / vehicle-triggered
- SSC mode 2 / SIPTO¹⁾ above RAN
- SSC mode 3 / -
- UPF / S/P-GW relations are only examples and can be different



1) SIPTO: Selective IP Traffic Offload

SA / NSA:


- SSC mode 1 / vehicletriggered
- SSC mode 2 / SIPTO¹⁾
 above RAN
- SSC mode 3 / -
- → Break-before-make, vehicle-triggered



SA / NSA:

- SSC mode 1 / vehicletriggered
- SSC mode 2 / SIPTO¹⁾ above RAN
- SSC mode 3 / -
- → Break-before-make, vehicle-triggered


Optionally, lower AS can be contacted before disconnect (any use case that can benefit?)



SA / NSA:

- SSC mode 1 / vehicletriggered
- SSC mode 2 / SIPTO¹⁾
 above RAN
- SSC mode 3 / -
- → Break-before-make, network-triggered


Also, for SSC mode 2 the new AS can be contacted before disconnect



SA / NSA:

- SSC mode 1 / vehicletriggered
- SSC mode 2 / SIPTO¹⁾
 above RAN
- SSC mode 3 / -
- → Make-before-break, network-triggered


How to decide when to disconnect from old gateway?



SA / NSA:

- SSC mode 1 / vehicletriggered
- SSC mode 2 / SIPTO¹⁾
 above RAN
- SSC mode 3 / -
- → Make-before-break, network-triggered

How to decide when to disconnect from old gateway?




Session Continuity: 3GPP Gateway Switching

5G SA (5GC)	5G NSA, 4G (EPC)	Trigger	Drawback
SSC mode 1	Release / re-establish PDN session in vehicle CCU ¹⁾	Client application and/or OS e.g. based on Cell- / Tracking Area- / PLMN ID (cross-MNO) change	 Service interruption of up to one second Triggering at wrong location will just select the same gateway again
SSC mode 2	SIPTO ²⁾ above RAN	Tracking Area Update from RAN but other policies possible	 Service interruption of up to one second Needs special support in EPC
SSC mode 3	Not available (<u>tricks</u> with two APNs possible for our trials)	Tracking Area Update from RAN but other policies possible	Complexity when two gateways are usedUnclear when to release the "old" gateway


- 1) CCU: Communication Control Unit (vehicular 3GPP network router)
- 2) SIPTO: Selective IP Traffic Offload




- No cross-border/-MNO handover no problem:
 - Just configure "Local Breakout Routing" when vehicle establishes new data network connection in visited network
- SSC mode 1 and 2 can do transition from Home to Local Breakout Roaming
 - We now have uninterrupted cross-border/-MNO handover and do not want to "break" it due to gateway switching
- Does SSC mode 3 work across PLMNs?
 - If not, should 3GPP Core specs be adapted for it?




- No cross-border/-MNO handover no problem:
 - Just configure "Local Breakout Routing" when vehicle establishes new data network connection in visited network
- SSC mode 1 and 2 can do transition from Home to Local Breakout Roaming
 - We now have uninterrupted cross-border/-MNO handover and do not want to "break" it due to gateway switching
- Does SSC mode 3 work across PLMNs?
 - If not, should 3GPP Core specs be adapted for it?




- No cross-border/-MNO handover no problem:
 - Just configure "Local Breakout Routing" when vehicle establishes new data network connection in visited network
- SSC mode 1 and 2 can do transition from Home to Local Breakout Roaming
 - We now have uninterrupted cross-border/-MNO handover and do not want to "break" it due to gateway switching
- Does SSC mode 3 work across PLMNs?
 - If not, should 3GPP Core specs be adapted for it?



- No cross-border/-MNO handover no problem:
 - Just configure "Local Breakout Routing" when vehicle establishes new data network connection in visited network
- SSC mode 1 and 2 can do transition from Home to Local Breakout Roaming
 - We now have uninterrupted cross-border/-MNO handover and do not want to "break" it due to gateway switching
- Does SSC mode 3 work across PLMNs?
 - If not, should 3GPP Core specs be adapted for it?



- No cross-border/-MNO handover no problem:
 - Just configure "Local Breakout Routing" when vehicle establishes new data network connection in visited network
- SSC mode 1 and 2 can do transition from Home to Local Breakout Roaming
 - We now have uninterrupted cross-border/-MNO handover and do not want to "break" it due to gateway switching
- Does SSC mode 3 work across PLMNs?
 - If not, should 3GPP Core specs be adapted for it?





MEC Architecture - Part II

Maciej Muehleisen Ericsson (ERI) maciej.muehleisen@ericsson.com

7th of June 2021, 5GCroCo Lunchtime Web-Seminar 6 (Hosted by 5G-PPP)



The project has received funding from the European Union's Horizon 2020 research and innovation programme under grant agreement No 825050-5GCroCo



Outline Part II


- Service Continuity: Discovering and Switching Servers
- Use Case Examples: Triggers for Switching & Dealing with Outage
- Controlled End-to-End QoS Across Multiple MNOs
- Joined Management and Orchestration of Virtual Network Functions and MEC-hosted Application Servers
- Open Tasks for Deliverable D3.3 (March 2022)
- Completed and Planned Trials
- Summary & Conclusion



Servers

 Changing the gateway usually means changing the IP address


- Usually Network Address Translation (NAT) is also used
- Normal TCP connections break when IP address changes because source IP/port are part of unique ID
- Multipath TCP and QUIC use unique IDs and survive IP address changes
 - So far, only considered to stay connected to old (upper) Application Server
- Many applications quickly recover from broken TCP connections (demo)



Servers

 Changing the gateway usually means changing the IP address


- Usually Network Address Translation (NAT) is also used
- Normal TCP connections break when IP address changes because source IP/port are part of unique ID
- Multipath TCP and QUIC use unique IDs and survive IP address changes
 - So far, only considered to stay connected to old (upper) Application Server
- Many applications quickly recover from broken TCP connections (demo)



Servers

 Changing the gateway usually means changing the IP address


- Usually Network Address Translation (NAT) is also used
- Normal TCP connections break when IP address changes because source IP/port are part of unique ID
- Multipath TCP and QUIC use unique IDs and survive IP address changes
 - So far, only considered to stay connected to old (upper) Application Server
- Many applications quickly recover from broken TCP connections (demo)



Servers

 AECC describes lookup tables, IP Anycast and DNS as solutions

- Anycast not preferred as it requires network support
- Lookup table in vehicle hard to keep up to date
- DNS-based solutions:
 - Source-IP based with
 - Network information based
 - Who operates the DNS servers?



Servers

 AECC describes lookup tables, IP Anycast and DNS as solutions

 Anycast not preferred as it requires network support

 Lookup table in vehicle hard to keep up to date


DNS-based solutions:

Source-IP based with

 Network information based

 Who operates the DNS servers?

Area



Servers

 AECC describes lookup tables, IP Anycast and DNS as solutions

 Anycast not preferred as it requires network support

 Lookup table in vehicle hard to keep up to date


DNS-based solutions:

Source-IP based with

 Network information based

 Who operates the DNS servers?

Area





 AECC describes lookup tables, IP Anycast and DNS as solutions

Anycast not preferred as it requires network support


 Lookup table in vehicle hard to keep up to date

DNS-based solutions:

Source-IP based with

 Network information based


Who operates the DNS servers?



Use case Examples: Triggers for Switching &


Dealing with Outage

Step	Event	Example Triggers		Application Server		Gateway	
			Old	New	Old	New	
0	Precondition		Χ		Χ		
1	Optional: Contact new server before gateway/server switching	To be determined if possible	X	X	X		
2	Disconnect from old gateway (SSC mode 1 and 2 only)	CCU trigger (SSC mode 1); MME/SMF trigger (SSC mode 2)					
3	Connect to new gateway	CCU trigger (SSC mode 1); MME/SMF trigger (SSC mode 2 and 3)	X	X	X	X	
4	Use new application server	Detecting that a new gateway is being used	X	X	Χ	Χ	
5,6	Stop using old application server	To be determined; if Step "6,5" is done first, it can serve as (part of the) trigger		X	X	Χ	
6,5	Disconnect from old gateway (SSC mode 3 only)	To be determined		X		X	




Use case Examples: Triggers for Switching & Dealing with Outage - HD Mapping SSC Mode 1






Use case Examples: Triggers for Switching & Dealing with Outage - HD Mapping SSC Mode 1

				Applica Serv		Gateway		У	
्र हिं Event		Trigger		MNO 1		MNO 1		MNO	
			Upper	Lower	MNO 2	Upper	Lower	0 2	
0	Precondition		Χ			Χ			
1	Disconnect from MNO 1 upper gateway Change of Tracking Area (vehicle triggered / SSC mode 1); wait for pending transmissions to finish and do not start new ones								
2	Connect to MNO 1 lower gateway	Disconnect completed (see row above)					Χ		
3	Connect to HD map application server (IP address discovered through DNS request)	Connect completed (see row above)		X			X		
4	Request pending User Story 3 downloads	Connected to HD map application server (see row above)		X			X		-
Intra-MNO gateway and application server switching complete									
5-8	Same as for intra-MNO; instead of Tracking Area change, also Mobile Network Code change can be used as trigger				X			Χ	
Cross-border / -MNO gateway and application server switching complete									




Use case Examples: Triggers for Switching & Dealing with Outage - ACCA SSC Mode 1 or 2

ANTICIPATED COOPERATIVE COLLISION AVOIDANCE (ACCA)




Use case Examples: Triggers for Switching & Dealing with Outage - ACCA SSC Mode 1 or 2

		Event	Trigger	Application Server			Gateway			
	Step			MNO 1		MNO	i i	NO 1	MNO	
				Upper	Lower) 2	Upper	Lower) 2	
	0	Precondition		Χ			Χ			
	1	Disconnect from MNO 1 upper	Change of Tracking Area detected in CCU (vehicle							
		gateway	triggered / SSC mode 1) or trigger from network							
			(SIPTO above RAN / SSC mode 2)							
	2	Connect to MNO 1 lower gateway	Disconnect completed (see row above)					X		
	3	Connect to lower Geoservice (IP	Connect completed (see row above), to be		Χ			Χ		
		address discovered through DNS	further evaluated what triggers are possible							
		request)	with SIPTO above RAN / SSC mode 2							
Intra-MNO gateway and application server switching complete										
	4-6	Same as for intra-MNO; instead of	e as for intra-MNO; instead of Tracking Area change, also Mobile Network Code X X							
		change can be used as trigger; no	ge can be used as trigger; no need to change the gateway for public Internet							
		access (keep Home Routed Roaming for public Internet access)								
	Cross-border / -MNO gateway and application server switching complete									




Use case Examples: Triggers for Switching & Dealing with Outage - Device-side Routing

```
wwan0: flags=4305<UP,POINTOPDINT,RUNNING,NOARP,MULTICA
        inet 192.168.193.18 netmask 255.255.255.252
        inet6 fe80::d0e:ce8a:9601:a00b prefixlen 64
        unspec 00-00-00-00-00-00-00-00-00-00-00-00-
        RX packets 2 bytes 612 (612.0 B)
        RX errors 0 dropped 0 overruns 0 frame 0
        TX packets 6 bytes 848 (848.0 B)
        TX errors 0 dropped 0 overruns 0 carrier 0
wwp0s20f0u6i10: flags=4305<UP, POINTOPOINT, RUNNING, NOAF
        inet 192.168.193.2 hetmask 255.255.255.
       RX errors 0 dropped 0 over UE ROUTE Selection
TX packets 6 bytes 24
        TX errors 0 dropped 0 overruns 0 carrier 0
```




- MEC simplifies providing bounded latencies within one MNO
 - Only if transport network for Core is "controlled", not "best effort"
- It cannot be assumed that all vehicles are served by same MNO
- Connecting MNOs over the public Internet will not result in controlled QoS
- Solution co-created with data center provider Equinix
- Also published in <u>5GAA</u> <u>MEC whitepaper</u>






- Solution 1: Move MEC hosts from MNO to collocation data centers (DCs) (aka "shared DCs")
- Obtain controlled links from MNO to collocation DCs
- Within DC highperformance networks will not be a bottleneck
- Some MNOs are also WAN and/or DC provider






- Solution 2: Move MEC hosts and gateways from MNO to collocation DCs
- Assure transport connecting Core nodes also covers the DCs (technically likely the same as for Solution 1)
- Within DC, highperformance networks will not be a bottleneck
- Some MNOs are also WAN and/or DC provider







- Solution 3: Controlled connection between MNOs
- Security is always an issue but here it is pointed out that MEC hosts usually do not have public IP addresses
- Some MNOs are also WAN and/or DC provider
- Sec. gateways: MEChosts usually do not have public IP addresses
 - Also for Sol. 1 & 2, but emphasized here






- Some MNOs are also WAN and/or DC provider
- Technically, the solutions are equal
- Selecting one depends on
 - If MNOs are also in the WAN / DC business
 - Costs WAN / DC providers ask for their service
- It is an economic / organizational decision












- Current deployments usually use full virtualization for Network Functions (NFs) forming the Core
 - E.g. OpenStack or VMWare
- It appeared logical to use the same for MEC-hosted ASs




- Hyperscale Cloud Providers (HCPs) (e.g. AWS, MS Azure, Google) use Containerizes ASs
- They are now partnering with MNOs to also deploy to MEC hosts
- MNOs might still be using VM-based NF deployment




- Hyperscale Cloud Providers (HCPs) (e.g. AWS, MS Azure, Google) use Containerizes ASs
- Mobile network vendors are also taking this path
 - → Cloud Native
- How to coordinate the MANO systems
 - "Meta-MANO"?
 - Master-slave?
 - ..
- Different HCPs have different MANO interfaces



- Hyperscale Cloud Providers (HCPs) (e.g. AWS, MS Azure, Google) use Containerizes ASs
- Mobile network vendors are also taking this path
 - → Cloud Native
- Who provides the MANO system?



- Hyperscale Cloud Providers (HCPs) (e.g. AWS, MS Azure, Google) use Containerizes ASs
- Mobile network vendors are also taking this path
 - → Cloud Native
- Who provides the MANO system?



- A transition from full VMs to Containerbased (Cloud-native) deployment is taking place
- Using same virtualization technique does not imply using same MANO
 - Esp. applies for (Graphical) User Interface ((G)UI)
- It is for now open how different MANO systems can cooperate in context of MEC

Scenario	VNF MANO	MEC-hosted Application Server MANO		
VM-based for VNFs and	VM-based (e.g. OpenStack-	Same as for VNFs (VM-		
application servers	based)	based)		
VM-based for VNFs, Container-	VM-based (e.g. OpenStack-	Container-based (usually		
based for application servers	based)	Kubernetes-based)		
Container-based for VNFs and	Container-based (usually	Container-based (usually		
application servers, separate	Kubernetes-based)	Kubernetes-based)		
MANO systems of same kind				
Container-based for VNFs and	Container-based (usually	Same as for VNFs (Container-		
application servers, common	Kubernetes-based)	based)		
MANO system				



Open Tasks for Deliverable D3.3

- Tie all loose ends to obtain:
 - Solutions fitting all use cases (even more than the 3 5GCroCo ones)
 - An evolutionary path
 - Starting with non-standalone 5G New Radio (and 4G where yet no 5G coverage)
 - Leading to standalone 5G New Radio with SSC mode 3
- Device-side routing and reactions to "triggers"
 - Esp. UE Route Selection Policies (URSP)?
- Better point out differences / benefits of IPv6
- Realistic topologies:
 - Draft "reference" topologies for different "MNO classes" and ask MNOs if they confirm and/or how to adjust
- Capture evolution of MNO/Hyperscale Cloud Provider cooperation



Completed and Planned Trials

Done (Round 1, HD Mapping & ACCA):

- MEC vs. public Internet performance:
 - 15% faster download of 6.7 MByte tiles for HD Mapping
 - 5 ms shorter App. Level Latency compared to server in Frankfurt (AWS) for ACCA

Planned (Round 2, all ACCA, selected vehicles/modems):

- MEC-to-MEC information exchange (<u>already used in Montlhery</u>)
- Break-before-make (SSC mode 1) gateway switching
- Make-before-break (SSC mode 3) gateway switching (emulated)
- DNS-based server discovery & switching



Summary & Conclusion

- MEC consists of the two major challenges
 - Gateway switching (session continuity)
 - Server switching (service continuity)
- The first is covered by 3GPP SSC modes 1-3
 - Some open questions regarding SSC mode 3 in single- and multi-MNO scenario
- Many open questions on the device side (expected to clarify in 2021) prevented to have a final architecture
- Solutions are very use-case-dependent why we would like to have a general proposal:
 - Consider use case classes / communication patterns, e.g.
 - Request/reply
 - Publish/subscribe (message broker)



Thanks!!

Maciej Muehleisen Ericsson (ERI) maciej.muehleisen@ericsson.com



To know more: http://5gcroco.eu

Follow us in twitter: @5GCroCo Connect in LinkedIn Subscribe to our Newsletter

Contact us: coordinator@5gcroco.eu



